

NEW FEATURES

■ SLIDE DOOR CLOSER SYSTEM

1. General

- The slide door closer system fully closes the slide door automatically if the slide door is ajar.
- In this system, the slide door closer relay detects the state of the slide door by way of the latch switch and the pawl switch that are provided in the door closer assembly. Then, the relay actuates the door lock motor to fully close the slide door.
- The slide door control relay supplies power to the slide door closer relay via the junction switch.
- This system provides a canceling mechanism that forcefully opens the slide door by operating the inside or outside handle of the slide door, in the event the door lock motor stops due to the jamming of a foreign object while the slide door closer system is operating.

